

Please type a plus sign (+) inside this box → ☐

PTO/SB/05 (4/98)  
Approved for use through 09/30/2000. OMB 0651-0032  
Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

# UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No. 367.38589X00

First Inventor or Application Identifier Andy PHELPS

Title AUDIO APPARATUS

Express Mail Label No.

## APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

ADDRESS TO:

Assistant Commissioner for Patents  
Box Patent Application  
Washington, DC 20231

1. ☒ \* Fee Transmittal Form (e.g., PTO/SB/17)  
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 12]  
(preferred arrangement set forth below)
  - Descriptive title of the Invention
  - Cross References to Related Applications
  - Statement Regarding Fed sponsored R & D
  - Reference to Microfiche Appendix
  - Background of the Invention
  - Brief Summary of the Invention
  - Brief Description of the Drawings (if filed)
  - Detailed Description
  - Claim(s)
  - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 4]  
1
4. Oath or Declaration [Total Pages 2]  
1
  - a. ☒ Newly executed (original or copy)
  - b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))  
(for continuation/divisional with Box 16 completed)
    - i. ☐ DELETION OF INVENTOR(S)  
Signed statement attached deleting  
inventor(s) named in the prior application,  
see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission  
(if applicable, all necessary)
  - a. ☐ Computer Readable Copy
  - b. ☐ Paper Copy (identical to computer copy)
  - c. ☐ Statement verifying identity of above copies

## ACCOMPANYING APPLICATION PARTS

7. ☒ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. § 3.73(b) Statement ☒ Power of  
(when there is an assignee) Attorney
9. ☐ English Translation Document (if applicable)
10. ☒ Information Disclosure ☒ Copies of IDS  
Statement (IDS)/PTO-1449 Citations
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)  
(Should be specifically itemized)
13. ☐ \* Small Entity ☐ Statement filed in prior application  
Statement(s) Status still proper and desired  
(PTO/SB/09-12)
14. ☒ Certified Copy of Priority Document(s)  
(if foreign priority is claimed)
15. ☒ Other: FIGS. 1-5

\* NOTE FOR ITEMS 1 & 13 IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY  
FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT  
IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).

16 If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No: \_\_\_\_\_

Prior application information: Examiner \_\_\_\_\_ Group / Art Unit: \_\_\_\_\_

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

## 17. CORRESPONDENCE ADDRESS

☒ Customer Number or Bar Code Label

020457

or ☐ Correspondence address below

(Insert Customer No. or Attach bar code label here)

Name

Address

City

State

Zip Code

Country

Telephone

Fax

Name (Print/Type)

Carl H. BRUNDIDGE

Registration No. (Attorney/Agent)

29,621

Signature

Date

May 23, 2000

Burden Hour Statement This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231

**AUDIO APPARATUS****5 Background of the Invention**

This invention relates to audio apparatus, and in particular audio apparatus for radiating an ultrasonic pressure wave with a modulated audio signal.

Audio spotlighting, using a parametric audio system, provides a means for projecting highly directional beams of audible sound. This technology employs the non-linearity of a compressible material (such as air) to create audible by-products from inaudible ultrasound. This technique exploits an acoustic phenomenon called self-demodulation where low frequency audio beams of high directivity are generated from a high amplitude ultrasonic beam that has been modulated with an audio signal. Self-demodulation generates new frequencies in the received sound spectra based on the envelope frequency (i.e. the required audio signal) in a process akin to AM demodulation. Thus this technique provides a beam of audio sound with the focused directional properties of the original ultrasonic carrier beam, allowing distant targeting of specific listeners. This technique can produce predictable and controllable levels of audio sound and, despite the relatively weak effect of self-demodulation, is capable of generating substantial sound amplitudes due to the narrow spatial distribution of the acoustic energy.

The transmitted modulated ultrasonic wave can be considered as a collimated primary wave consisting of an amplitude modulated wave of pressure where the primary pressure wave is defined by

$$1) \quad p_1 = P_1 E(t) \sin(\omega_c t)$$

where  $P_1$  is the amplitude of the primary beam pressure,  $\omega_c$  is the carrier frequency and  $E(t)$  is the modulation envelope. For an amplitude modulated signal  $E(t)$  is equal to  $(1 + mg(t))$  where  $m$  is the modulation depth and  $g(t)$  is the audio signal.

5

As a result of  $p_1$  interacting with the air the modulated audio signal demodulates creating an audible secondary pressure wave  $p_2$  given by

$$10 \quad 2) \quad p_2(t) = \frac{\beta P_1^2 A}{16\pi\rho_0 c_0^4 z \alpha} \frac{\partial^2}{\partial t^2} E^2(\tau)$$

where  $\beta$  is the coefficient of nonlinearity ( $\beta_{\text{air}} = 1.2$ ),  $\rho_0$  is the ambient density of the medium,  $c_0$  is the small signal wave propagation speed,  $A$  is the beam's cross-sectional area,  $z$  is the axial distance,  $\alpha$  is the absorption coefficient of the medium. So, for example, where  $c=343$  m/s,  $\rho_0=1.2\text{kg/m}^3$ ,  $\alpha = 0.6$ , and  $A=5\times 10\text{m}^3$ , a 140dB ultrasound wave modulated with a 1kHz signal would produce about 71dB of audible sound at 1m.

The power of the resultant audio signal is proportional to the second derivative of the square of the modulation envelope. As a result significant coloration (i.e. a shift of signal power with respect to frequency) and distortion are introduced onto the demodulated audio signal as a result of the interaction of the ultrasonic wave with the non-linear medium. The coloration of the signal results in the low frequency audio components being suppressed by approximately 12dB/octave; this is represented by the second derivative term of the modulation envelope. The distortion of the signal is represented by the square of the modulation envelope.

Processing the audio signal prior to modulation can minimise the effects of coloration and distortion that result from the interaction of the ultrasonic wave

with the non-linear medium. The processing typically comprises a double integration filter to compensate for coloration of the audio signal and a square root operation to compensate for the distortion of the audio signal.

- 5 However, for the self-demodulation to occur high ultrasonic sound pressure levels are required. To generate these high pressure levels it is necessary to generate the ultrasonic pressure levels at or close to the resonant frequency of the transmitting transducer. Correspondingly the frequency response of the transducer can vary dramatically at this frequency. The variable transducer  
10 frequency response can significantly affect the quality of the demodulated audio pressure wave.

- Figure 1, plot A shows the frequency spectrum of a white noise input signal constrained between 300 and 4000 Hz prior to modulation with an ultrasonic  
15 carrier signal. An example of the effects of self-demodulation and transducer conversion upon the input signal, using a typical transducer having a measured frequency response shown in figure 2, is shown in figure 1, plot B.

- The frequency response of a transducer can be flattened at the resonant  
20 frequency. However this requires considerable damping to be added to the transducer, and a corresponding drop in ultrasonic pressure level. This in turn would require a transducer with a large radiating surface area, which is not suitable for small devices, for example a mobile communication device and in particular a radiotelephone.

25

### **Summary of the Invention**

- In accordance with an aspect of the present invention there is provided audio  
apparatus comprising a modulator for modulating a first ultrasonic signal with  
an audio signal to provide a second ultrasonic signal; a transducer for  
30 converting the second ultrasonic signal into an ultrasonic pressure wave for

transmission into a non-linear medium to allow demodulation of the ultrasonic pressure wave and thereby generate an audio pressure wave representative of the audio signal; processing means for modifying the audio signal to compensate for the demodulating properties of the non-linear medium; and  
5 means for modifying the audio signal to compensate for the conversion characteristics of the transducer.

This provides the advantage of enabling the effects of the demodulation process and the transducer conversion characteristics on the audio signal to  
10 be minimised. This can allow the size of the transducer to be reduced while retaining the performance of the transducer.

Typically the means for modifying the audio signal to compensate for the conversion characteristics of a transducer is a transducer response filter.  
15

Most preferably the processing means comprises a double integration filter and a square root operator. As the operator processes the audio signal non-linearly the characteristics of the second filter are preferably derived empirically by tone adjustment for the required frequency range of the audio  
20 signal.

The invention will now be described, by way of one example only, with reference to the accompanying drawings, in which:

## 25 **Brief Description of the Drawings**

Figure 1, plot A shows the frequency spectrum of a test audio input signal to an audio apparatus according to one embodiment of the present invention;

Figure 1, plot B shows the frequency spectrum of figure 1, plot A after self-demodulation without correction;  
30

Figure 2 shows a typical measured frequency response of a suitable transducer for use in audio apparatus according to an embodiment of the present invention;

5

Figure 3 shows a radiotelephone having audio apparatus according to an embodiment of the present invention;

Figure 4 shows audio apparatus according to an embodiment of the present invention;

10

Figure 5, plot A shows the frequency spectrum of the test audio signal output after self-demodulation with correction for self-demodulation;

Figure 5, plot B shows the frequency spectrum of the test audio signal output from audio apparatus according to an embodiment of the present invention.

15

### Detailed Description of the Invention

Figure 3 shows a radiotelephone 1 with audio apparatus 2, a speech decoder 3, a channel decoder 4, a receiver 5 and an antenna 6. In operation the receiver 5 receives a speech encoded digital signal 20 from a base station (not shown) via antenna 6. The receiver 5 demodulates the received digital signal 20 and passes the demodulated signal 21 to channel decoder 4 which corrects for errors that may have occurred during the transmission process by using error protection bits encoded within the received signal. The receiver 5 typically samples the received signal 20 at 8 kHz. The decoded digital signal 22 is provided to speech decoder 3 which decodes the speech and passes the digital decoded signal 23 to audio apparatus 2 to generate an acoustic representation of the received speech signal as described in detail below. The audio apparatus 2 may be mounted within the radiotelephone 1. Typically

20

25

30

however, to obtain the required audio power levels and to support hands free use of the radiotelephone 1, the audio apparatus 2 is mounted separately to the radiotelephone 1, for example, in conjunction with a hands free kit or a car kit for hands free use of a radiotelephone in a car.

5

Figure 4 shows the audio apparatus 2 which comprises a double integration filter 7, a transducer response filter 8, a DC shifter 9, an up-sampler 10, a square root operator 11, a modulator 12, an ultrasonic signal source 13, a digital to analogue converter 14 and an ultrasonic transducer 15.

10

The audio apparatus 2 is a parametric device that radiates an inaudible ultrasonic pressure wave with an audio signal modulated onto the ultrasonic pressure wave. The transmitted ultrasonic wave interacts with air (i.e. a compressible non-linear medium) to cause the ultrasonic wave to self-demodulate, thereby causing the modulated audio signal to become audible.

15

Digital signal 23 is provided to double integration filter 7, which boosts the low frequencies by 12 dB/octave akin to integrating the signal twice. Double integration filter 7 compensates for the effects of coloration that occur during the self-demodulation process, and is linear in nature. Typically, the double integration filter 7 is a simple recursive filter. The double integration filter 7 provides the double integrated digital signal 24 to transducer response filter 8.

20

The transducer response filter 8 corrects for characteristics of the ultrasonic transducer 15, as described in detail below. The transducer response filter 8 provides the corrected signal 25 to DC shifter 9.

25

The DC shifter 9 re-scales the data and shifts the voltage of the corrected digital signal 25 so that all signal voltages are positive, thus ensuring the

square root operation only has to work on positive values, thereby avoiding complex filtering.

The DC shifted signal 26 is provided to up-sampler 10. The up-sampler 10 re-samples the 8 kHz signal at typically 120 kHz. The purpose of up-sampler 10 is to increase the frequency range of the signal in preparation for the square rooting of the signal. A consequence of square rooting the received signal is the creation of an infinite series of harmonics. For distortion to be eliminated all these harmonics must be reproduced. Therefore, to ensure harmonics above 4 kHz are reproduced the signal is re-sampled at a higher frequency. Sample rates other than 120 kHz may be used dependant on the operating frequencies of the ultrasonic transducer. The re-sampled signal 27 is provided to the square root operator 11.

The square rooting operator 11 compensates for the effects of distortion that occur during the self-demodulation process, and is non-linear in nature.

The square root operator 11 is typically performed by means of a look up table, as is well known to a person skilled in the art.

The square rooted signal 28 is provided to modulator 12 for modulation with an ultrasonic signal 29 from ultrasonic signal source 13. To minimise the risk of harm to humans or animals the ultrasonic frequency should be higher than approximately 40kHz. Due to increased signal absorption by the air at higher frequencies the upper highest feasible frequency limit is typically of the order of 200kHz.

The digital modulated ultrasonic signal 30 is provided to digital to analogue converter 14 for converting the digital signal 30 to a representative analogue signal. The analogue modulated ultrasonic signal 31 is provided to ultrasonic



transducer 15. Transducer 15 radiates the modulated ultrasonic signal as an inaudible ultrasonic pressure wave.

To obtain the required ultrasonic pressure levels required for self-demodulation to occur the transducer 15 will typically be chosen to have its resonance frequency at the frequency of the ultrasonic carrier signal 29.

For a 40 kHz ultrasonic signal a suitable transducer is the MuRata MA40B8S. This transducer has a frequency response as shown in figure 2, which has a narrow resonance band at 40 kHz. To obtain the required power levels a plurality of transducers will typically be required, for example 19 transducers will provide 55 dB's of audio speech signal.

As the square root operator 11 is non-linear it is not possible for the transducer response filter 8 to have a single optimum filtering characteristic for all frequencies. Therefore, the transducer response filter 8 is determined empirically for a required frequency range. For example, if the resultant spectra of the self-demodulated signal shows a gradual power drop from 300 Hz to 4 kHz after correction for self-demodulation, the transducer response filter 8 is selected to boost the signal over this frequency range. The characteristics of the transducer response filter are therefore, typically, the inverse response of the resultant spectra of the self-demodulated signal. The transducer response filter is designed typically using a recursive filter design package, for example the Yule-Walk package, which models the transducer response filter characteristics using the inverse of the self-demodulated signal.

Typically the transducer response filter characteristics are determined during the manufacture of the audio device. However, it is possible for the

characteristics of the transducer response filter to be determined dynamically, for example while during use of the audio device.

Figure 5, plot A shows the transducer conversion effect upon the input signal shown in figure 1, plot A. Figure 5, plot B shows the corrected spectrum using a transducer response filter 8 empirically derived using figure 5, plot A for determining the effect of the transducer conversion. For different frequency and modulation depths the square root non-linear operator 11 will vary the effects of the transducer conversion and accordingly different frequency and modulation depths will require the transducer response filter 8 to be modified empirically as described above.

The transducer response filter 8 is typically a simple recursive filter.

The present invention may include any novel feature or combination of features disclosed herein either explicitly or implicitly or any generalisation thereof irrespective of whether or not it relates to the presently claimed invention or mitigates any or all of the problems addressed. In view of the foregoing description it will be evident to a person skilled in the art that various modifications may be made within the scope of the invention. The applicant hereby gives notice that new claims may be formulated to such features during prosecution of this application or of any such further application derived therefrom. For example, it will be appreciated that an analogue audio signal can be processed and modulated with an ultrasonic carrier signal, also that the pre-processing filters and/or operator can be used to process the audio signal after modulation of the audio signal.


**What is claimed is:-**

1. Audio apparatus comprising a modulator for modulating a first ultrasonic signal with an audio signal to provide a second ultrasonic signal; a transducer for converting the second ultrasonic signal into an ultrasonic pressure wave for transmission into a non-linear medium to allow demodulation of the ultrasonic pressure wave and thereby generate an audio pressure wave representative of the audio signal; processing means for modifying the audio signal to compensate for the demodulating properties of the non-linear medium; and means for modifying the audio signal to compensate for the conversion characteristics of the transducer.
2. Audio apparatus according to claim 1, wherein the first ultrasonic signal is amplitude modulated with the audio signal.
3. Audio apparatus according to claim 1, wherein the first ultrasonic signal is equal to or greater than 40 kHz.
4. Audio apparatus according claim 1, wherein the processing means comprises a double integration filter and a square root operator.
5. Audio apparatus according to claim 4, wherein the means for modifying is disposed between the double integration filter and the square root operator.
6. Audio apparatus according to claim 1, wherein the means for modifying is a digital filter.
7. Audio apparatus according to claim 1, wherein the characteristics of the means for modifying are empirically derived by tone adjustment.

8. A radiotelephone having audio apparatus according to claim 1.
9. A portable radio device having audio apparatus according to claim 1.

**ABSTRACT**

Audio apparatus comprising a modulator 12 for modulating a first ultrasonic  
5 signal 29 with an audio signal to provide a second ultrasonic signal 30; a  
transducer 15 for converting the second ultrasonic signal 30 into an ultrasonic  
pressure wave for transmission into a non-linear medium to allow  
demodulation of the ultrasonic pressure wave and thereby generate an audio  
pressure wave representative of the audio signal 28; processing means 11 for  
10 modifying the audio signal to compensate for the demodulating properties of  
the non-linear medium; and means 8 for modifying the audio signal to  
compensate for the conversion characteristics of the transducer 15.



000250" 6E09/360






FIG.2








FIG.5

## DECLARATION AND POWER OF ATTORNEY - PATENT APPLICATION

As a below named inventor, I hereby declare: that my citizenship, residence and post office address are as stated below; that I verily believe I am the original, first and sole inventor (if only one is named below) or a joint inventor (if plural inventors are named below) of the invention entitled: AUDIO APPARATUS

the specification of which   X   is attached hereto

\_\_\_\_\_ was filed on \_\_\_\_\_ as Application  
Serial No. \_\_\_\_\_ and was amended on  
\_\_\_\_\_.

I hereby state that I have reviewed and understand the contents of the above-identified specification, including the claims, as amended by any amendment referred to above. I acknowledge the duty to disclose information which is material to the examination of this application in accordance with Title 37, Code of Federal Regulations, §1.56(a). I hereby claim foreign priority benefits under Title 35, United States Code, §119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

Prior Foreign Application(s)			Priority Claimed
Number	Country	Day/Month/Year Filed	Yes / No
9913848.9	GREAT BRITAIN	14 JUNE 1999	YES

I hereby claim the benefit under Title 35, United States Code, §120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, §112, I acknowledge the duty to disclose material information as defined in Title 37, Code of Federal Regulations, §1.56(a) which occurred between the filing date of the prior application and the national or PCT international filing date of this application;

Application Serial No	Status-patented, pending or abandoned
-----------------------	---------------------------------------

I hereby appoint as principal attorneys: Donald R. Antonelli, Reg. No. 20,296; David T. Terry, Reg. No. 20,178; Melvin Kraus, Reg. No. 22,466; William I. Solomon, Reg. No. 28,565; Gregory E. Montone, Reg. No. 28,141; Ronald J. Shore, Reg. No. 28,577; Donald E. Stout, Reg. No. 26,422; Alan E. Schiavelli, Reg. No. 32,087; James N. Dresser, Reg. No. 22,973, Carl I. Brundidge, Reg. No. 29,621; and Paul J. Skwierawski, Reg. No. 32,173; to prosecute and transact all business in the Patent and Trademark Office connected with this application and any related United States and international applications.

Please Direct all Communications to:

Direct Telephone Calls To:


Antonelli, Terry, Stout & Kraus, LLP  
Suite 1800  
1300 North Seventeenth Street  
Arlington, Virginia 22209

(703) 312-6600

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

(Full Name)  
ANDREW PHELPS

(Signature)



Date: 15/5/00 | Inventor: ANDREW PHELPS

Residence: SOUTHAMPTON, HAMPSHIRE | Citizenship: BRITISH

Post Office Address:

103 MALMESBURY ROAD, SHIRLEY,  
SOUTHAMPTON, SO15 5FP

(Full Name)

(Signature)

Date: | Inventor:

Residence: | Citizenship:

Post Office Address:

(Full Name)

(Signature)

Date: | Inventor:

Residence: | Citizenship:

Post Office Address: